

# Videoscope system


**User Manual** 

# **Table of Contents**

System Outlook2
Getting started3
System Environment4
Multi-function Keys5
Menu Operations
• Delete All7
Deleting a Specific Photo7
• AV Output8
Setup Date/Time8
Setting Time Display10
• Language10
• TV System11
Auto Power Off11
Operating Instructions12
• Power On/Off12

Taking Photos1	
Video Recording1	1
Viewing Photo/Video1	1
• Zoom-in1	4
Mirror View1	1
Specifications1	!


# System Outlook



- 1 Record
- 2 Pa Snap
- 3 U Power

- OK OK / Menu
- Esc / ZOOM / MIRROR
- USB port
- SD Port
- TV Out
- AC Jack
- Light Adjustment
- Insert tube Connector
- Hanger Hole

# **Getting started**






Insert the insert tube into the connector according to the direction of the red align dot and tighten the screw nut.



Step 2

Press and hold the power button for 3 seconds until the image is displayed on the monitor.



# Step 3

Aim the camera lens at the selected area. Press to capture a image, or press to start recording a video.

# **System Environment**

This product provides three simple working modes: Preview, Browse and Manual Mode.

## Preview Mode

When the system turns on, the preview mode will be activated automatically, user can take pictures and record videos.

## Browse Mode

Press 🖊 🔻 to view photos and videos stored in the SD card and also delete files.

### Manual Mode

User may complete their preferences setup and file management here.

NOTE: THE SYSTEM RETURNS TO PREVIEW MODE AUTOMATICALLY AFTER 150 SECONDS WITHOUT ANY RESPONSE IN MANUAL MODE.

# **Multi-function Keys**

Each button on the system performs a unique function depending on the Mode when system is operated.

FUNCTION	IN PREVIEW MODE	IN BROWSE MODE	IN MANUAL MODE	
<b>A</b>	Switch to Browse Mode to view photos and videos	Move to previous photo or video	Move up in the main manual	
•	Switch to Browse Mode to view photos and videos	Move to next photo or video	eo Move down in the main manual	
ок	swith to Manual Mode	Play/Pause video	Execute selected command	
ESC	Press once to Zoom in 2x. Press and hold 3 seconds for Mirror View	Return to Preview Mode	Return to Preview Mode	
۵	Capture a photo	N/A	N/A	
<b>8</b>	Press once to start recording video, press again to stop recording	Delete photo	N/A	

# Menu operations

#### Overview

Press OK button into Manual Mode and select the setting needs to be adjusted.

#### MENU

DELETE ALL AV OUTPUT DATE / TIME LANGUAGE TV SYSTEM AUTO POWER OFF

#### **DELETE ALL**

Delete all files in the SD card.

## **AV OUTPUT**

To send the video signal out through the AV port. The monitor will turn black until you execute this command again.

### DATE / TIME

To set up system time.

### LANGUAGE

To select the operation language.

## TV SYSTEM

Set up your video format.

#### **AUTO POWER OFF**

Select 5, 10, 15, or 30 minutes to activate system auto power off setting.

## Delete All (Delete all files in SD)

Step 1 Press OK in Preview mode.

IMAGE STATUS: SHOWING THE MAIN MANUAL.

Step 2 Press ▲ or ▼ to "DELETE ALL" command.

Step 3 Press OK.

IMAGE STATUS: "YES" OR "NO" OPTION APPEARS.

Step 4 Use ▲ or ▼ to select "YES" "NO".

Step 5 Press OK to delete all files.





# Deleting a specific photo (Browse mode only)

Step 1 Enter Browse mode, then press ▲ or ▼ to find out the photo or video you wish to delete.

Step 2 Press 🚉.

IMAGE STATUS : DELETE CONFIRM.

Step 3 Press OK to delete selected file, or press ESC to skip.



#### **AV OUTPUT**

Step 1 Plug in the AV cord into the AV socket located on the right side of the system.

NOTE: PLEASE PLUG THE OTHER END OF THE AV CORD INTO THE "AV IN" SOCKET ON THE EXTERNAL MONITOR.

- Step 2 Press OK in Preview mode.
- Step 3 Press ▲ or ▼ to select to "AV OUT" option.
- Step 4 Press OK.

IMAGE STATUS : IMAGE WILL BE TRANSMITTED TO THE EXTERNAL MONITOR.



## Date/Time Setup

- Step 1 Press OK in Preview mode.
- Step 2 Press ▲ or ▼ to select Date/Time.
- Step 3 Press OK to activate the setting.
- Step 4 Press to increase the number or to decrease
- Step 5 Press ▼ for next adjustment.
- Step 6 Repeat step 4 and 5 until the correct time/ date are set up.
- Step 7 Press OK to complete the setting.



# **Setting Time Display**

- Step 1 Press OK in Preview mode.
- Step 2 Press ▲ or ▼ to select "DATE/TIME".
- Step 3 Press OK.
- Step 4 Press ▲ or ▼ to "Display" option.
- Step 5 Press to switch the "Display" function between ON/OFF.

IMAGE STATUS : PRESS ONCE FOR ON, PRESS AGAIN FOR OFF.

- Step 6 Press OK to complete set up.
- Step 7 Press ESC to return to Preview mode.







with Time Display On

# Language

- Step 1 Press OK in Preview mode.
- Step 2 Press ▲ or ▼ to select "LANGUAGE".
- Step 3 Press OK.
- Step 4 Press ▲ or ▼ to select the operation language.
- Step 5 Press **OK**.

# LANGUAGE ENGLISH FRANCAIS DEUTSCH ITALIANO ESPANOL

# TV system

# TV System

- Step 1 Press OK in Preview mode.
- Step 2 Press ▲ or ▼ to select to "TV SYSTEM".
- Step 3 Press **OK**.
- Step 4 Press ▲ or ▼ to select NTSC/PAL.



# Auto power off


- Step 1 Press OK in Preview mode.
- Step 2 Press ▲ or ▼ move to "AUTO POWER OFF" option.
- Step 3 Press OK.
- Step 4 Press ▲ or ▼ to select desired time length, to activate press OK, or select OFF to skip.



# Operations

#### Power On/Off

- Step 1 To turn on the system, press and hold the  $\mbox{\em 0}$  button for 3-5 seconds until system start.
- Step 2 Press and hold the **U** button for 3~5 seconds to turn off the system.



BATTERY CAPACITY

SD CARD MEMORY CAPACITY

# **Taking Photos**

Press 🖸 button in Preview Mode to take a photo.

IMAGE STATUS : RETURNS TO PREVIEW MODE AUTOMATICALLY AFTER PHOTO IS TAKEN.



## **Recording Video**

Step 1 Press button to start recording video .

IMAGE STATUS: RECORDING TIME WILL APPEAR AT THE LEFT BOTTOM THE SCREEN.

Step 2 Press the button again to stop recording.

IMAGE STATUS: RECORDING TIME DISAPPEARS.



# Viewing Photo/Video

Step 1 Press ▲ or ▼ in to Preview Mode.

IMAGE STATUS: DISPLAYING THE LATEST PHOTO/VIDEO.

Step 2 Press ▲ or ▼ again to view from the first or last photo/video in the SD card.

IMAGE STATUS: ALL FILES WILL BE STORED CHRONOLOGICALLY.





NOTE: WHEN VIEWING VIDEOS, THE VIDEO WILL BE PLAYED AUTOMATICALLY UNTIL IT ENDS AND THEN THE NEXT PHOTO OR VIDEO WILL BE DISPLAYED.

#### Zoom-In\*

Press ﷺ button once, the screen will show 2X zoom in view while ⊕2.0x will show on the night button of the screen.





BEFORE ZOOM-IN AFTER ZOOM-IN

Press again to return to the original view

## Mirror effect\*

Press and hold to button for 3 seconds to activate the mirror view while are will show on the right bottom of the screen, press and hold for 3 seconds again to return to original view.





WITHOUT MIRROR EFFECT

WITH MIRROR EFFECT

# Specifications

System							
Dimension	117.5 x 207 x 37mm	Frame Rate	30 fps				
Weight	383g	Exposure	Automatic				
Power	Rechargeable Li-Polymer Battery 3.7V Power supply AC 100-240V 50-60Hz Power consumption DC5.5 2A	White Balance	Fixed				
Display	3.5 TFT LCD	Charging Temperature	10°C-40 °C				
Recording Medium	SD Card (4G included)	Working Temperature	0°C-60 °C				
Video Output Format	NTSC & PAL	Storage Temperature	0°C-60 °C				
Video Output Interface	AV out						
Compression Format	Compliant with MPEG4						
Still Image Storage Format	JPEG						

# Caution

- This product is designed for industrial use only. Do not use the system for human or any other biological inspection.
- ① Do not disassemble the product, it might cause shock hazard and damage the unit.
- Use only recommended components or accessories. Unauthorized accessories and components may cause damage to this product.
- To avoid danger, do not put the insert tube into any flammable liquid or gas. Oil Passed: Unleaded Gasoline, Machine Oil, Diesel, Brake Oil (DOT 4), Transmission Oil, Neutral Cleanser.
- ① Do not use this product in a fuel tank or other dangerous environment such as a gasoline or alcohol storage tank.
- ① Do not bend the insert tube over 180 degrees during usage or storage.

- ① Do not remove the SD card while capturing photos or videos. This can cause a loss of the image or video recorded and may damage the SD card.
- Avoid direct exposure to sunlight for long period of time. Store the system in a cool, dry and well-ventilated place.

